# **User's Manual**

HDR-3000T

The default password is 0000.



### Notice

Thank you for purchasing a HUMAX product. Please read this user's manual carefully to be able to safely install, use and maintain the product at maximum performance. Keep this user's manual next to your product for future reference. The information in this user's manual is subject to change without notice.

#### Copyright © 2014 HUMAX Corporation)

Not to be copied, used or translated in part or whole without HUMAX's prior consent in writing except approval of ownership of copyright and copyright law.

#### Meaning of Symbols



To reduce the risk of electric shock, do not remove cover (or back). No user serviceable parts inside. Refer servicing to qualified service personnel.



This symbol indicates dangerous voltage inside the product that presents a risk of electric shock or personal injury.



This symbol indicates important instructions accompanying the product.

#### Warnings, Cautions and Notes

Throughout the whole manual, pay special attention to the following marks that indicate hazardous situations.

#### Warning

Indicates a hazardous situation which could result in serious injury

#### Caution

Indicates a situation which could damage the equipment or other apparatus  ${\bf Note}$ 

Indicates additional information to make the user aware of possible problems and information of any importance to help understand, use and maintain the installation.

#### Warranty

The warranty does not cover parts which may become defective due to misuse of the information contained in this manual.

#### 'WFFF' Instructions

This product should not be disposed with other household wastes at the end of its working life. Please separate this from other types of wastes and recycle it responsibly to promote the sustainable reuse of material resources. This will prevent possible harm to the environment or human health from uncontrolled waste disposal.

#### Domestic users:

Please contact either the retailer where you purchased this product or their local government office for details of where and how they can take this item for environmentally safe recycling.

#### **Business users:**

Contact your supplier and check the terms and conditions of the purchase contract. This product should not be mixed with other commercial wastes for disposal.

#### Trademarks

- Manufactured under license from Dolby Laboratories.
   Dolby and the double-D symbol are trademarks of Dolby
- HDMI, the HDMI Logo, and High-Definition Multimedia interface are trademarks and registered trademarks of HDMI Licensing LLC.



This item incorporates copy protection technology that is protected by U.S. patents and other intellectual property rights of Rovi Corporation. Reverse engineering and disassembly are prohibited.

Note: The model name is located on the bottom of this product.

## For Your Safety

### Safety Instructions

#### 1. POWER SUPPLY

- Operate this product only from the type of power supply shown on the marking label. If you do not know the type of power supplied to your home, contact your local power company.
- Disconnect the power supply before you start any maintenance or installation procedures.

#### 2. OVERLOADING

 Make sure that the wall outlet, extension cord and adapter have a sufficient power rating for the appliance. If not, this can cause an electric fire shock.

#### 3. LIQUID

• Do not expose this product to liquids. Do not put objects filled with liquid on the product.

#### 4 CLEANING

- Disconnect the product from the wall outlet before you clean it.
- Use a moist cloth to clean the product. Do not use solvents. Wipe the surface gently with a soft cloth as it may get scratched.

#### 5. VENTILATION

- Make sure that the slots on top of the product are not blocked. It is necessary to have a sufficient airflow into the unit.
- · Do not put electronic equipment on the product.
- Do not put objects on the product. This will block the ventilation or cause damage to the surface.

#### 6. ATTACHMENTS

 Do not use any unsupported attachments as these may be hazardous or cause damage to the product.

#### 7. LIGHTNING, STORM OR NOT IN USE

 Unplug the product from the wall outlet and disconnect the antenna during a thunderstorm or when left unattended and unused for long periods of time. This will prevent damage to the unit due to lightning and power-surges.

#### 8. EXTRANEOUS OBJECTS

 Do not insert anything through the openings in the unit, where they can touch dangerous voltage points or damage parts.

#### 9. REPLACEMENT OF PARTS

 When replacement of parts is required, be sure the service technician uses replacement parts specified by the manufacturer or those that have the same characteristics as the original part. Unauthorised substitution may result in additional damage to the unit.

## 10. CONNECTION TO THE SATELLITE DISH LNB/CABLE TV SIGNAL/AERIAL

 Disconnect the power supply before you connect or disconnect the cable from the satellite dish/ cable TV signal/aerial. If not, this can cause damage to the LNB/cable TV line/aerial.

#### 11. CONNECTION TO THE TV

 Disconnect the power supply before you connect or disconnect the cable from the TV.
 If not, this can cause damage to the TV.

#### 12. LOCATION

- Place the product indoors to avoid exposure to lightning, rain or sun. Do not place it near a radiator or heat register.
- Keep at least 10 cm clearance from any other appliances susceptible to electromagnetic influences such as a TV or a VCR.
- If you place the product on a rack or a bookcase, make sure that there is adequate ventilation and that you have followed the manufacturer's instructions for mounting.
- Do not place the product on an unstable surface where it can fall. A falling product can cause serious injury to a personnel and serious damage to the appliance.

#### 13. Environment

- Attention should be drawn to the environmental aspects of battery disposal.
- Care is required for the use of this apparatus in tropical and/or moderate climates.

### Cautions and Warnings

#### 1. To avoid damage of the power cord or plug

- Do not modify or process the power cord or plug arbitrarily.
- · Do not bend or twist the power cord.
- Make sure to disconnect the power cord while you hold the plug.
- Keep heating appliances as far as possible from the power cord to prevent the cover vinyl from melting.
- The mains plug, as a disconnection device, shall remain readily accessible by the user.
- All-pole main switch shall remain readily operable. (For products with power switch)

#### 2. To avoid electrical shock

- · Do not open the main body.
- Do not insert metal or inflammable objects inside the product.
- · Do not touch the power plug with wet hands.
- · Disconnect the power cord in case of lightning.
- Unplug the power cable before you install the antenna cable.

### 3. To avoid damage of product

- Do not use the product when it is out of order. If you continue to use the product when defective, this may cause serious damage. Make sure to contact the customer service centre if the product is out of order.
- Do not insert metal or alien substance into the slots for the modules. It may cause damage to the product and reduce its life span.
- Do not overly pile objects on the product. It may cause cracks, deformation and discoloration.

### 4. To avoid damage of the hard disk drive (PVR only)

- Do not move the product or turn the power off suddenly while the hard disk drive is running.
- The company shall not be liable for any corruption of data on the hard disk drive caused by carelessness or misuse of the user.

### Contents & Accessories

## Contents

Notice1
For Your Safety2
Contents & Accessories3
Contents Accessories
Getting Started4
Product Overview Connections Remote Control Wizard Mobile Apps
Watching TV8
Home Simple Guide Programme Detail Smart Search TV Guide TV Guide App
Recording13
Instant Recording Scheduled Recording Recording Conflict Scheduling with Mobile App Playing Recorded Programmes

Media Center15
Direct Access to Media Files Playing Media Files Playing Files by Storage Playing with Mobile APP
TV APPS19
Settings20
General Settings Network Settings PVR Settings System Settings Channel Settings
Appendix26
Specification

Trouble Shooting

Glossary

**HUMAX Customer Support** 

Open Source Software Notice Supplier's declaration of conformity

## Accessories





/ Batteries

User Manual






AC Adaptor

W-LAN STICK


*Note:* Accessories may vary according to area.

### **Product Overview**



- 1 **VOLUME:** Changes the audio volume.
- **2 CHANNEL:** Changes the channel or page.
- 3 STANDBY: Switches between operation and standby modes.
- 4 USB: Connect a USB memory device.
- 5 LED: Lights red in standby mode and blue in operation mode.
- 6 HOLE: Lights blue when the network connection functions properly.

*Note:* The blue light may not emit depending on the product.




- 1 RF IN: Connect to a TV antenna.
- **2 RF OUT:** Connect to the TV or VCR using an RF cable.
- 3 VIDEO/AUDIO: Use an RCA cable to connect to the TV.
- 4 SPDIF: Use an SPDIF cable to connect to the digital audio device.
- 5 HDMI: Use an HDMI cable to connect to the TV.
- 6 ETHERNET: Connect a LAN cable.
- 7 USB: Connect a USB memory device.
- 8 POWER: Connect the AC adaptor.

Note: The image may differ from the actual product.

### Connections

This section describes how to connect your product to match your particular devices and to gain optimum signal quality.

*Warning:* Connect all devices before you plug any power cords into the wall outlet. Always turn off the product, TV and other devices before you connect or disconnect any cables.



#### Note:

- If you encounter any problems setting up your product, please contact your local retailer or HUMAX Customer Service.
- Connecting your TV directly to the audio/video output of the product will assure a more vivid picture and enhance your viewing enjoyment.

#### HDMI CEC

HDMI CEC (Customer Electronics Control) lets you to control the TV and HDMI CEC supported devices through the HDMI cable.

If your TV supports HDMI CEC, it will turn on or off automatically when the product is turned on or off. However, turning the TV on or off does not affect the product.

### Connecting the Antenna

Connect the aerial to the ANTENNA IN.

### Connecting the TV

2-1 Using an HDMI cable

For the best picture quality, use an HDMI cable to connect to the TV.

2-2 Using an RCA cable

Using an RCA cable provides a lower resolution because the HD signal cannot be transmitted.

#### Note:

- Use an S/PDIF cable to connect to the audio system for digital audio.
- Programmes restricted by Digital Rights Management (DRM) may not be viewed via the HDMI cable. For such programmes, use an RCA cable.


### Connecting the Network

- 3-1 Connecting to the LAN
- Use the Ethernet cable to connect the product and the LAN router.
- Set the options for the LAN.
   (Go to HOME > SETTINGS > Network Settings to set the network options)
- 3-2 Connecting to the Wireless LAN
- 1. Use the USB WLAN stick to connect to the wireless LAN.
- 2. Go to HOME>SETTINGS>Network Settings>Configure WLAN and set the options for the wireless LAN.

#### Note:

- We recommend the network connection over a direct LAN.
- Make sure that the distance between the Wireless LAN access point and the product is not too far away. This may lower the quality of service.


## Remote Control



	TV APPS	Goes to HUMAX TV APPS
ψ	STB	Switches between operation and standby modes
	TEXT	Enters the digital text service
	SUB	Sets the subtitle language
	AUDIO	Sets the audio language
1	Playback Control Buttons	≪ Fast Rewind, ► Play, ► Fast Forward,             ■ Stop, II Pause, ® Record,
	SEARCH	Runs Smart Search
	PLUS	Displays option menus
	ARROW Buttons	Moves the cursor up, down, left or right
	ОК	Selects a menu or confirms a selection
	EXIT	Exits all On-Screen Display (OSD) screens
	ВАСК	Returns to the previous channel or the previous screen
	VOL +/-	Changes the audio volume
	НОМЕ	Displays the HOME menu
	GUIDE	Displays the programme guide
	P ^/~	Changes the channel or page
2	COLOUR Buttons	For interactive applications
	NUMERIC	(0-9)
	MUTE	Mutes audio
	TV/RADIO	Switches between TV and radio modes

### Inserting Batteries

Insert the batteries matching the plus(+) and minus(-) at each end.  $\label{eq:plus} % \begin{subarray}{ll} \end{subarray} \begin{subarra$ 



### Remote App

You can control your HUMAX product right from your mobile devices just as using the actual remote control.

Phone	Remote	Use all buttons on the actual remote control.	
	Keyboard	Enter the text conveniently.	
	Simple	Use main buttons.	
Tablet	Full	Use all buttons on the actual remote control.	

Note: See page 7 for downloading Remote App.

### Wizard

The installation wizard operates automatically when you power on the product for the first time or do factory default in menu.

Note: If you exit the installation wizard without fully completing the channel searching procedure, you may not have all of the channels available. In this case, go to HOME-SETTINGS>Channel Settings>Search Channels and search for more channels

### 1. Region

Select the state you currently live in.

#### 2. Network Connection

Make sure that the LAN cable is connected to the Ethernet port or the wireless LAN is connected. Configure the network setting.

### 3. Privacy Policy

Agree or disagree to share anonymous data about how you use your products. If you agree, this is very helpful for us to make better products.

### 4. Channel Search

Set the search options and then search channels. You can search channels automatically or manually. Save the found channels when the search is complete.

#### 5. Result

The result of the installation wizard will show. Select EXIT.

## Mobile Apps







Remote App

TV Guide

Media Player

You can enjoy almost features on your mobile device as well as on your HUMAX product.

#### Remote App

You can use your mobile device as a remote control from anywhere in your home.

#### TV Guide

You can schedule recordings or reminders remotely on your mobile device.

#### Media Player

You can play media files from HUMAX product or other home network devices right on your mobile device.

## Downloading Mobile App

- Go to Google play or iTunes App Store to download HUMAX Mobile Apps.
- 2. Search by keyword HUMAX.
- 3. Install the HUMAX Apps on your mobile device.

#### Note:

- HUMAX Apps may not guarantee best performance for all mobile devices.
- Both HUMAX product and mobile device should be connected to the same network.
- Some features are not available outside home network.
- HUMAX Mobile Apps require Android 4.0 and later, and iOS 6 and later.

### Home


You can go to the home menu by pressing the **HOME** button wherever you are. From the home menu, you can reach Live TV, TV Guide, Recordings, Media Center, TV Apps and Settings.

- Press the HOME button to go to the home menu wherever you are.
- To see the recent list, press the ▼ button.
   You can easily go to the recently accessed contents or menus.

## Simple Guide

You can change channels, see what's on later or watch catch-up programmes when available.

- Press the OK button while watching live TV to display Simple Guide.
- Press the ▲/▼ button to change a channel.
   Whenever you change a channel, thumbnail appears.
- Press the EXIT button to hide the Simple Guide.



### Watching Live TV

- Select a programme and press the **OK** button.
- · You can also enter the channel number directly.

### Pausing and Rewinding Live TV (TSR)

Time Shifted Recording (TSR) allows you to pause a live programme and return later where you left off. To pause a live programme, wait for a few seconds after changing the channel.

The TSR function temporarily records the programme you are watching to the hard disk drive automatically. TSR lasts for 120 minutes.



#### To pause the programme

- 1. Press the PAUSE button.
- Press the PLAY button to watch from the pausing point.
   Pause makes a time gap between the live broadcasting point and watching point.

#### To watch missed scenes

- 1. Press the FAST REWIND button.
- 2. Press the PLAY button at the point where you want to start watching.

### To skip scenes

Press the **FAST FORWARD** button when there is a time gap between the current watching point and the live broadcasting point.

If you reach the live broadcasting point while fast forwarding, the programme

automatically plays at normal speed.

### Setting TV Options

- Press the PLUS button while watching live TV to change the resolution, display format, audio language and subtitle language.
- Press the SUB button to set the subtitle language.

### Changing Channel Group

- 1. Press the **PLUS** button.
- 2. Select a channel group and press the **OK** button.

### Seeing What's On Later

- 1. Press the ▶ button to see what's on later.
- 2. Select a programme and press the **OK** button.

  Programme detail appears. You can set recordings or reminders.

### Watching Catch-Up Programmes


Press the ◀ button to watch catch-up programmes.

Catch-up programmes are accessible only when the recorded programmes are available.



## Programme Detail

- To find out more about the programme you are watching, press the OK button.
- Press the **OK** button again to display programme detail.
   You can watch an episode of a catch-up programme or set reminders or recordings for future programmes.



Episode Icons		Programme Icons	
(L)	Reminder (blue) Scheduled recording (red)	HD	HD programme
	Playback possible		Parental guidance programme
0	Recording in progress	Q <sub>opy</sub>	Blocked by digital recording management
SL	Series recording		Locked programme
<b>D</b>	Daily	DOLBY. DIGITAL PLUS	Dolby digital plus
<b>D</b>	Weekly	DOLBY.	Dolby Digital

### **Smart Search**

You can search episodes of your favourite programmes and look up related programmes by a simple button press. This feature is available while watching live TV, playing back a recorded programme or on TV Guide

- Press the SEARCH button. Related programmes are listed.
- For more search, enter a keyword.

**Note:** Enter at least three characters to search programmes or media files. If you enter less than three characters, channels and Apps are searched.



### TV Guide



You can see the programme schedule of each channel, and schedule recordings or reminders for future programmes.

- Press the GUIDE button.
- Select a programme from next or catch-up programmes and press the OK button to display the programme detail.



### Watching Live TV

Select a programme and press the **OK** button or enter the channel number directly.

*Note:* Press the P^/v button to change a page.

Changing Channel Group

- 1. Press the PLUS button.
- 2. Select the channel group and press the **OK** button.

### **Quick Navigation**

- 1. To move to a certain date, long press the **◄/▶** button.
- 2. Select a date and press the **OK** button.

### Seeing What's on Later

Press the ▶ button to see the next programmes.



#### Setting Reminders or Recordings

- 1. Select a programme and press the **OK** button.
- 2. Select an episode in the left column.
- 3. Select RECORD WHOLE SERIES, RECORD THIS PROGRAMME or SET REMINDER and press the OK button.

(L)	Reminder (blue)	0	Recording in process
(L)	Recording (red)	SL)	Series recording

#### Note:

- If the programme conflicts with another programme, adjust the scheduling appropriately. See page 14 for more information.
- If the channel is locked, you will be prompted to enter your password.
   The default password is 0000. If you have forgotten your password, please contact your local distributor.

### Changing Programme Genre

- Press the PLUS button when the cursor is on a next programme.
- Select a genre and press the **OK** button.

### Watching Catch-Up Programmes

- 1. Press the ◀ button to watch catch-up programmes.
- 2. Select a programme and press the **OK** button.

You can catch up with the programmes you have missed or watch recordings.



## TV Guide App

You can see the programme guide on your mobile device as well as on your TV. You can download HUMAX TV Guide App at Apple iTunes and Google Play. See page 7 for downloading HUMAX TV Guide App.

*Note:* For information how to use, refer to the instructions in HUMAX TV Guide App. When you use TV Guide App for the first time, you need to pair your HUMAX product with your mobile device.

### Pairing

- 1. Tap HUMAX TV Guide App on your mobile device to open. Pairing message appears.
- 2. Select the product to pair with the mobile device.
- 3. Enter the registration code. See page 22 for retrieving the registration code.

### Remote Recording

You can schedule recordings or reminders on your HUMAX product remotely using your mobile device.

**Note:** You need to register and sign in to myhumax.net to use this feature. See page 19 for information how to create myhumax.net account.

- 1. Sign in to with myhumax.net ID and password.
- 2. Tap GUIDE to go to TV Guide.
- 3. Select a future programme.
- 4. Tap **Record this programme** or **Set reminder**. You can schedule recordings for whole series if the programme is part of a series.

#### Recording

You can record programmes instantly and schedule recordings in **TV Guide**, **Programme Detail** or **Recordings**. You can record up to four programmes while watching a live TV and a live TV programme on your mobile device at the same time.

## **Instant Recording**

Press the **RECORD** button to record the current programme. Press the **STOP** button to stop recording.

### Extending recording duration

- 1. Press the **RECORD** button while recording.
- 2. Set the duration manually or select till the end of the current or next programme.

EXTEND RECORDING DURATION

Extend the recording duration by setting it manually.

104 Channel 4 (14:32-15:01, 29mins)

Record till (~15:01)

Record till the end of "Come Dine with Me" (~15:00

#### Note:

- Recording will continue until the end of the current programme.
   If it ends within ten minutes, the recording will continue until the end of the next programme.
- · Recording continues for two hours if there is no programme information.

## **Scheduled Recording**

You can schedule recordings in TV Guide, Programme Detail and Recordings.

#### TV Guide

Press the **HOME** button and select **TV GUIDE**. Select a future programme and press the **RECORD** button.

Note: See page 11 for scheduling recordings or reminders in TV GUIDE.

### Programme Detail

Press the ▶ button while watching a programme.

Select a future programme listed on the left to record and press the **OK** button. Select a recording option.

### Recordings

You can schedule recordings or reminders manually.

- 1. Press the **HOME** button. Select **RECORDINGS** and **SCHEDULE**.
- 2. Select ADD A SCHEDULE.
- 3. Set a schedule manually.
- 4. Select **OK** and press the **OK** button.



## Editing Schedule

You can delete or reschedule the scheduled programmes.

- 1. Press the HOME button. Select RECORDINGS and SCHEDULE.
- 2. Select a scheduled programme.
- 3. Press the PLUS button.
- 4. Select **Delete** or **Reschedule**.

**Note:** You can set the padding time to record programmes with extra recording time. Go to HOME > SETTINGS > PVR Settings > Recording Options.

## **Recording Conflict**

### **Recording Conflict**

A recording conflict occurs:

- · Case 1 when you try to start a new recording while recording.
- Case 2 when a new recording conflicts with the previously scheduled recordings.

Select one of the recordings to cancel.

### **Tuning Conflict**

A tuning conflict occurs when a scheduled recording is about to start while you are watching another channel.

A record notice will pop up 30 seconds before the scheduled recording starts.

- YES: The channel will change at the start time and the recording will start.
- NO: The scheduled recording will be canceled.

## Scheduling with Mobile App

You can schedule recordings or reminders remotely on your mobile device. You can download HUMAX TV Guide App at Apple iTunes and Google Play. See page 7 for downloading HUMAX TV Guide App.

- 1. Open TV Guide App on your mobile device.
- 2. Go to **GUIDE** and tap the programme you want. The programme detail appears.
- Tap RECORD THIS PROGRAMME.
   You can reschedule the recordings or reminders in HOME > RECORDINGS
   > SCHEDULE.

#### Note:

- Make sure that HUMAX product and your mobile devices are connected to the same network.
- Log in the TV Guide App with the ID and password you registered in myhumax.net to schedule recordings and reminders.

## **Playing Recorded Programmes**

You can play the recorded programmes in RECORDINGS. The recordings are categorized by groups, PROGRAMME, CHANNEL, DAY OF WEEK so that you can find the recordings you want easily.

## Playing Recordings

- 1. Press the HOME button. Select RECORDINGS.
- 2. Select a recording and press the **OK** button.
- 3. Select **PLAY THIS PROGRAMME** and press the **OK** button. You can delete the recording or record whole series if the programme is part of a series.
- 4. Press the **OK** or **PLAY** button during playback, the play bar appears.



#### Playback Controls

<b>•</b>	Play	4	Fast rewind
II	Pause	-	Fast forward
	Stop		

#### Media Center

You can play video, music, photo files from the connected storage devices or home network devices on your TV. Make sure that the USB storage device or network is connected correctly.

Press the HOME button. Select MEDIA CENTER.

### Direct Access to Media Files

- 1. Select VIDEO, PHOTO or MUSIC.
- 2. Select a storage or network server. The recently played files appear.



#### Note:

- You cannot play the recently played files from the external storage which is already disconnected.
- HUMAX is not responsible for any data loss or file damage.
- Some playback control buttons may not function depending on the contents.

#### **Supported File Formats**

- · Video: MP4, VOB, AVI, ASF, MKV, MPEG-2TS
- Photo: JPEG, PNG, BMP, GIF
- Music: MP3

**Note:** Certain files may not play depending on file formats or video and audio codec.

## Playing Media Files

### Playing Video

Select a video file and press the **OK** button.



<b>•</b>	Play	-	Fast rewind
II	Pause	-	Fast forward
	Stop	+	Subtitle option

#### Changing Subtitle Option

- 1. Press the PLUS button when the play bar is on the screen.
- 2. Set the subtitle option.

Note: Subtitle may not be available for some video files played over the network.

### Playing Photo

Select a photo file and press the **OK** button. Photo slideshow starts.



<b>•</b>	Play	II	Pause
5	Exit slideshow	+	Play mode


### Changing Play Mode

You can set the slideshow speed or background music during slideshow. Press the **PLUS** button.

- Slideshow Speed: Select the display time per photo in slideshow.
- Music Play: Select On to play music files during slideshow.

### Playing Music

Select a music file and press the  $\mbox{\bf OK}$  button. All files in the group will play successively.



<b>•</b>	Play	II	Pause
5	Exit music player	+	Play mode

#### Changing Play Mode

You can set the slideshow speed or background music during slideshow. Press the **PLUS** button.

- Repeat Option: Set the repeat option in the playlist.
- Play Mode: Select Normal or Shuffle.

### **Editing Files**

You can delete, copy, move files and change the storage. Select a file and press the **PLUS** button.

Delete	Delete the file.
Сору	Copy the file to the storage you want.
Move	Move the file to the storage you want.
Select	Select a file.
Select All	Select all files.

#### Note:


- When you copy or move a file to an external storage device, the file is copied to its root folder.
- Files may not be copied or moved if the storage is full or the file size is too large.
- Files on a network server cannot be edited.

## Playing Files by Storage

### Playing Files from Storage Device

You can play files from the storage devices such as internal or external HDD and USB storage devices.

- 1. Select a storage device.
- 2. Select VIDEO, MUSIC or PHOTO.
- 3. Select files you want to play.



#### Note:

- Use USB storage devices formatted by ext3, FAT or NTFS only.
- Do not disconnect the USB storage device during playback, the files or the USB storage device may be damaged.
- It is recommended to use the USB storage devices requiring external power supply.
- If the USB storage device is connected in standby mode, it will automatically be recognized when the product is turned on.
- HUMAX cannot guarantee compatibility with all USB storage devices and assumes no responsibility for any loss of data.

### Playing Files from DLNA Devices

Your HUMAX product is a home network device capable of sharing media files with other home network devices such as the PC, NAS or another HUMAX PVR when they are connected to the same home network.

You can play the video, music or photo files saved in your DLNA devices on your product when the DLNA device is connected to the same home network.

#### Connecting to Home Network

- 1. Press the **HOME** button. Select **SETTINGS** > **Network Settings**.
- 2. Set the options for the LAN or Wireless LAN.

Note: See page 21 for connecting to the network.

#### Playing Files from DLNA Devices

- 1. Select a DLNA device.
- 2. Select VIDEO, MUSIC or PHOTO.
- 3. Select files you want to play.

#### Note:

- The list of supported home network media servers will appear automatically.
- Home network media server software such as Window Media Player 12 must be installed and executed on the PC to share media files stored in the PC.
   The media files must be stored in the library folder of the PC.
- Refer to the instructions of your operating system for setting up DLNA server.
- You can share your media files even when you are away from home. Go to HOME > SETTINGS >Network Setting > Network Server and set Server Activation Time to On. Enter the time period to activate the network server even when the product is in standby mode.

### Playing Files from SAMBA Server

- 1. Select a SAMBA server.
- 2. Enter the ID and Password of the PC to access to the shared folders.
- 3. Play the files from the SAMBA server on your TV.

**Note:** Make sure that the settings in your Windows7 PC is ready to connect to the SAMBA server. Refer to the instructions of your operating system for setting up SAMBA server.

## Playing with Mobile APP

You can play the files from your HUMAX product or DLNA devices on your mobile device. You can download HUMAX Media Player App at Apple iTunes and Google Play.

- Check if your HUMAX product, DLNA devices and mobile devices are connected to the same network
- 2. Open HUMAX Media Player App.
- 3. Tap your HUMAX product in the storage list.
- 4. Tap a file to play.

## Sending to TV

You can send the media file you are watching on your mobile device to your TV so that you can see it on a big screen.

- Tap anywhere while watching on your mobile device to display icons on the screen.
- 2. Tap and select your HUMAX product. The media file plays on your TV.

#### Note:

- This function works only on the wireless network.
- · Performance of streaming content depends on network environment.
- · See page 7 for downloading HUMAX Media Player App.

### TV APPS

You can download TV Apps from App Market and enjoy them on your TV. Press the HOME button. Select **TV APPS**.



#### Note:

- · Apps may differ depending on the region or service providers.
- · You may need to agree to Privacy Policy before using certain Apps.
- TV APPS is subject to change without notice. HUMAX is not responsible for the content or the discontinuity of the services.

### Creating an Account

You can enjoy various contents TV APPS offers by creating an account.

- 1. Go to https://www.myhumax.net and create an account.
- 2. Follow the instructions for the account creation process.

Note: Up to four personal accounts can be created.

### Signing In

You can manage your own Apps by signing in with your account. Select user profile and enter the user password to sign in.

Note: Family account is provided as default.

### Signing in to SNS

You can sign in to your SNS account with the ID and password you registered in myhumax.net.

## **Downloading Apps**

You can download hundreds of Apps from App Market.

- 1. Select App Market.
- 2. Browse the App market and select an App you want.

## **Editing Apps**

Select an App and press the PLUS button.

- Delete: Delete the App.
- Move: Move the App to the location you want.

## **General Settings**

Press the HOME button. Select SETTINGS and then General Settings.

#### Parental Control

- Restriction of Access: You can block the programme if the programme is above the age limit.
- · Change Password: Enter a new password.
- Block Channel Settings: Set On if you want to block access to the Channel Settings you have previously made.

#### Note:

- · Enter the password to view the blocked programmes.
- The default password is 0000. If you have forgotten your password, please contact your local distributor.

### Video Setting

You can set the screen ratio, display format and screen resolution.

### **Audio Setting**

- S/PDIF: You can select the digital audio signal output.
- HDMI: You can select the digital audio signal for HDMI output.
- Audio Type: You can select the audio type.
- Lip-Sync Delay: You can adjust the sound difference between audio and video.

### On-Screen Display

- Info Display Time: You can set the duration the Simple Guide is displayed whenever you change the channel.
- Subtitle Font: You can set the subtitle font.

## **Privacy Policy**

You can agree or disagree to send HUMAX your watching information. Your watching information will be helpful for HUMAX to improve both product and service.

## **Network Settings**

Press the HOME button. Select SETTINGS and then Network Settings.

### Configuring LAN

- 1. Select Configure LAN.
- 2. Select your IP configuration type between DHCP and Manual.
  - DHCP: If you use a router or modem that has a DHCP (Dynamic Host Configuration Protocol) server function, select DHCP. The IP address will automatically be determined.
  - Manual: If there is no DHCP server on the network and you want to set the IP address manually, select Manual. Enter the values for IP Address, Netmask, Gateway Address and DNS Address.
- 3. Select APPLY to connect to the selected network and press the OK button.

#### Note:

- When entering the IP address manually, enter 3 digits in a row.
- The network is connected by wired LAN when both wireless and wired LAN are activated.
- · HUMAX recommends the network connection over a wired LAN.

## Configuring Wireless LAN

- 1. Select Configure WLAN.
- 2. Select the wireless LAN network and press the **OK** button.
- 3. Press the BACK button to save.

**Note:** If you choose a locked wireless network, you need to enter the password to proceed The network password is case-sensitive and cannot contain spaces.

### **Network Connection Status**

You can view the connection status of the local area network or the Internet. Select **RETRY** if either network is disconnected.

### **Network Server**

- Network Server: Set to On to share the live broadcast, recordings and media files saved in the internal HDD with other products that support DLNA-Digital Media Player.
- Rename Server: Enter a new name to change the server name.
- Server Status: You can see the information on network servers.
- Server Activation Time: When Server Activation Time is set to On, the
  network server remains active during the time period you have entered
  even when the product is in standby mode. You can share live broadcasts,
  recordings and media files without turning the product on.

**Note:** The server activation time you can enter may differ depending on the product.

#### File Share

- SAMBA Server: When SAMBA Server is set to On, the internal HDD can be accessed as a network disk drive from your PC. You can copy the video, music, photo files in the internal HDD to the PC storage.
- FTP Server: When FTP Server is set to On, you can copy the video, music, photo files in the internal HDD to the PC storage using the FTP client programme.
- Password: If Password is set, you can access the internal HDD only by entering the password.
- Download Folder: When Download Folder is set to Enable, you can copy
  the video, music, photo files in the PC to the download folder in the internal
  HDD.

## **PVR Settings**

Press the HOME button. Select SETTINGS and then PVR Settings.

#### IP EPG

Set to On to enjoy advanced EPG services over the Internet.

### Remote Recording

You can set up recordings on your  $\ensuremath{\mathsf{HUMAX}}$  product from your PC or mobile devices.

To use this feature, you need to register your product in the website.

- Go to https://www.myhumax.net and create an account and register your receiver.
- 2. To register your receiver, you need a registration code for certification. Select **Retrieve Registration Code** and press the **OK** button.
- 3. Enter the registration code in the website.

Note: IP EPG menu must be set to On to use Remote Recording.

- Update Period: Set the period to receive the recording schedule from the HUMAX server.
- Update Interval: Set the update interval.

### **Recording Options**

- Start Padding Time / End Padding Time: You can set the recording padding time to add extra recording time to the start and end.
- Repeat Recording: Set to On to record reruns of a programme.
- **Keep Recordings:** Set the programmes to remain. The other programmems will be deleted automatically.
- Auto Delete: Set to On to add old recordings to the list of TO BE DELETED.

### Playback Options

- Series Play: Set to On to play back all episodes of a programme successively.
- Instant Replay Time: Select the replay time.
- Skip Forward Time: Select the skip time.

### Storage

You can check the capacity of each storage or format the storage when necessary.

- · Internal HDD: Run the HDD test or format the storage.
- External Devices: To remove the storage, select Remove Storage Safely first.

Note: All data in the storage will be deleted after formatting.

## System Settings

Press the HOME button. Select SETTINGS and then System Settings.

### System Information

You can view the system information. Select **CHECK NEW SOFTWARE** to see if new software is available.

#### **Power Timer**

You can set the time the product powers on or powers off.

## Power Management

- Automatic Power Down: Select On to enter standby mode automatically if no user interaction occurs for 3 hours.
- Power Saving in Standby: Select On to inactivate certain functions and reduce the power consumption in standby to below 0.5W.

**Note:** A message will display 2 minutes before the product enters standby mode. If you ignore this message, the product enters standby mode automatically.

### HDMI-CEC

You can set your TV to turn or off automatically when the product is turned on or off.

#### Interactive TV Service

You can set HbbTV to On, the interactive TV services such as digital teletext, catch-up TV and EPGs are provided over both broadcast and internet.

### Factory Default

You can restore your receiver to factory settings. Shortly after you complete the factory default, the installation wizard will appear automatically.

**Warning:** Note that once you perform factory default, all user configured data will be reset.

## **Channel Settings**

Press the HOME button. Select SETTINGS and then Channel Settings.

## Setting Favourite Channels



*Note:* Press the **EXIT** button to exit. Press the **BACK** button to return to the previous screen.

Select the channels from the left column and press the PLUS button.

Add to favourite	Add to favourite channels.
Change Group	List channels in another channel group.
Select / Deslect All	Mark or release all channels.

Select the channels from the right column and press the PLUS button.

Remove	Remove from favourite group.
Move	Move the channel in the favourite group.
Change Favourite	Change to another favourite group.
Rename Favourite	Rename the favourite group.
Select / Deslect All	Mark or release all channels.

## **Editing Channel List**

You can delete, lock or rename channels in the channel list. Select a channel and press the **PLUS** button.



Delete	Delete channels from channel list.
Lock/Unlock	Lock channels to block access.
Rename	Change channel name.
Select/Deselect All	Mark or release all channels.
Change Group	To list the channels of another favourite group, press the <b>PLUS</b> button and select <b>Change Favourtie</b> . Select the group and press the <b>OK</b> button.

### Dynamic Channel Update

The channel list is updated automatically in real time. If there is no channel to update, a message will appear.

### Signal Test

You can check the signal strength and quality of the searched channels.

#### Automatic Channel Search

You can search channels automatically without entering any other information. When the channel search is complete, select **SAVE** and press the **OK** button to save the results.

**Note:** Select **STOP** and press the **OK** button to stop the channel search. The searched channels will remain.

#### Manual Channel Search

You can search channels manually by searching parameters.

- Channel: Select the channel.
- Frequency: Enter the frequency. The corresponding frequency value will be automatically displayed.
- Bandwidth: Select the bandwidth. Select 7MHz if your region is Australia.
- Network Search: Select On or Off.

## Specification

	Tuner & Channel	
Input Connector	F-Type, IEC 169-24, Female	
Frequency Range	470 MHz to 858 MHz	
Signal Level	-70 to -10 dBm	
Demodulation	OFDM	
Mode	DVB-T:2K, 8K	
FEC Mode	DVB-T: 1/2, 2/3, 3/4, 5/6, 7/8	
Guard Intervals	DVB-T: 1/4, 1/8, 1/16, 1/32	
	Audio/Video Decoding	
Audio Decoding	MPEG/MusiCam Layer I & II	
Audio Mode	Single channel/Dual channel/Joint stereo/Stereo	
Video Decoding	MPEG-2 ISO/IEC 13818 Transport Stream Specification	
Video Format	4:3, 16:9	
Video Resolution	1080p, 1080i, 720p, 576p, 576i	
- Memory		
Flash Memory	512MB	
RAM	DDR3 1GB	
Audio/Video In/Out		
Video	RCA, HDMI/HDCP	
Audio	Audio L/R, S/PDIF	

Data In/Out		
USB	USB 2.0 Host (5 V===0.5A) x 2EA	
File Format	JPEG, MP3	
	Hard Disk	
HDD	500GB/1TB	
	Power Supply	
Input Voltage	100V – 240V ~ 50/60Hz 0.9A	
Туре	Adaptor	
Power Consumption	12V === 2.0A (Standby under 0.5W)	
Protection	Separate internal fuse. The input should be protected against lightning.	
Physical Specification		
Size (w/h/d)	280 x 48 x 200 (mm)	
Weight	1.03 kg	
Operating Temperature	0 °C to +40 °C	
Storage Temperature	-10 °C to +70 °C	

*Note:* The specifications are subject to change without notice.

## **Trouble Shooting**

Before contacting the customer service center, make sure to read the tips below carefully. If the problem persists after you complete the following procedure, please contact HUMAX customer service for further instructions.

#### General

Problem	Possible Cause	What to Do
No message displayed on the front panel	Mains adaptor unplugged.  Mains socket switched off.	<ul> <li>Check the main power cable and make sure it is plugged into a suitable power outlet.</li> <li>Connect the power cable to a different power outlet.</li> </ul>
No picture (Nothing shows on the TV)	HDMI cable not securely connected.	<ul> <li>Make sure that the product is powered on and in operation mode.</li> <li>Make sure that the AV or HDMI cable is firmly connected to the TV.</li> <li>Check the brightness level of the TV.</li> <li>Check if the channel is currently on air. Contact the broadcaster to ensure that the channel is running.</li> <li>Check if the input source of your TV is set for the AV or HDMI depending on how your product is connected to the TV.</li> <li>Check the brightness of the TV.</li> </ul>
No picture (No channels)	Aerial is disconnected.  Aerial is damaged/misaligned.  Out of digital signal area.  Antenna is not positioned.	<ul> <li>Make sure that the product is powered on and in operation mode.         Press the STANDBY button.     </li> <li>Make sure that the AV or HDMI is firmly connected to the TV.</li> <li>Make sure that the antenna cable is properly connected to the product.</li> <li>Press the Input or Source button on the TV remote and select AV or HDMI mode depending on how your product is connected to the TV.</li> <li>Search channels again. Go to HOME &gt; SETTINGS &gt; Channel Settings &gt; Automatic Channel Search.</li> <li>Check if the channel is currently on air. Contact the broadcaster to ensure that the channel is running.</li> </ul>
Poor Picture Sound quality	Electro magnetics from electronic devices around the product can cause the issue. Poor/faulty HDMI cable	<ul> <li>Make sure there is no mobile phone or microwave oven near the product.</li> <li>Keep the power and the RF cables apart from each other.</li> <li>Adjust the antenna direction to get a better picture.</li> <li>Note: If the antenna is covered with snow, the RF is weakened by heavy rain, or the antenna position is changed by strong wind, the condition of the sound and picture may temporarily be poor. However, the poor sound and picture quality due to weather conditions cannot be accepted as a malfunction of product.</li> </ul>

Problem	Possible Cause	What to Do
No sound	AV/HDMI cables are not connected properly or faulty. Volume is set to minimum or mute.	<ul> <li>Check that your AV or HDMl cable is connected correctly.</li> <li>Check the volume levels of your TV and the product.</li> <li>Check if the product or TV is on mute.</li> <li>Check audio type or soundtrack option. (where applicable)</li> </ul>
No response to remote control	Low batteries	<ul> <li>Remove and reinsert the batteries in the remote control.</li> <li>Replace the batteries in the remote control for a new set.</li> </ul>
No password information		The default password is always 0000.
Channel search does not work	Aerial is disconnected. Aerial is damaged/misaligned. Out of digital signal area. Antenna is not positioned.	<ul> <li>Make sure that the antenna cable is properly connected to the product.</li> <li>[Terrestrial] Use the appropriate antenna capable of receiving VHF or UHF channels for your area.</li> </ul>
Cannot update the new software	Network is not set up.	<ul> <li>Check if the network is configured properly. You can check the network connection status by going to HOME &gt; SETTINGS &gt; Networks Settings &gt; Network Connection Status.</li> <li>Note: If your product stays connected to the network, everytime you turn off the product it will search for any updates available on air.</li> <li>To manually search for any updates available, go to HOME &gt; SETTINGS &gt; System Settings &gt; System Information and then select CHECK NEW SOFTWARE.</li> <li>To update the software via USB,         <ol> <li>Download the latest software version and save it to an empty USB memory stick.</li> <li>Please make sure the software is saved in the root of the USB stick.</li> <li>Insert the USB memory stick into HDR-3000T on a rear USB port.</li> <li>Go to Home &gt; Settings &gt; System Settings &gt; System Information and press the OK button on Check New Software.</li> <li>When the download progress stops it may take up to 5 minutes for it to restart so 'DO NOT TURN OFF HDR-3000T'</li> <li>To confirm successful update, please go to Home &gt; Settings &gt; System Settings &gt; System Information and check Software Version.</li> </ol> </li> </ul>
Product makes a humming noise	Fan is blocked	<ul> <li>Make sure that there is no dust around the fan.</li> <li>If the symptom persists, please call HUMAX customer service on 1300 737 937.</li> </ul>
Randomly Shuts itself off	Automatic Power Down Option On Timer is set	<ul> <li>Go to HOME &gt; SETTINGS &gt; System Settings &gt; Power Management and then check if Automatic Power Down is set to On.</li> <li>Go to HOME &gt; SETTINGS &gt; System Settings &gt; Power Timer and then check if Power Off Timer is set to On.</li> </ul>

## Recordings

Problem	Possible Cause	What to Do
Cannot schedule recordings or reminders	Conflict of recordings	<ul> <li>Check that there is a previous schedule conflicting with a new schedule.         Cancel one of the schedules.     </li> <li>HDR-3000T has 2 tuners. This allows you to record up to 4 different channels and watch another program that is in the sister channel of the program that is currently being recorded.</li> </ul>
Cannot record programmes	Full HDD Conflict of recordings	<ul> <li>The hard disk is full. Delete unnecessary programmes and make space for new recording.</li> <li>Check if recording conflicts with another channel. Stop the current recording or wait until the recording is finished.</li> <li>Check that the product is switched on when recording starts.</li> <li>If you are missing first or end bits of the program, set the padding time. Go to HOME &gt; SETTINGS &gt; PVR Settings &gt; Recording options and set the padding times.</li> <li>Check if your product recognizes problems with the HDD. Go to HOME &gt; SETTINGS &gt; PVR Settings &gt; Storage, select the storage, and run the HDD test.</li> </ul>
Cannot play back on live TV.		Playing back on live TV is only available after 30 seconds you have been in the channel.
Cannot change channels while recording.	Conflict of recordings	HDR-3000T has 2 tuners. This allows you to record up to 4 different channels and watch another program that is in the sister channel of the program that is currently being recorded.
How to set the padding time		• If you are missing first or end bits of the programme, set the padding time. Go to HOME > SETTINGS > PVR Settings > Recording Options and set the padding times.
How enter passive mode		Go to HOME > SETTINGS > System Settings > Power Management and set Power Saving in Standby to On.

## Playback

Problem	Possible Cause	What to Do
How to edit recorded programmes		Go to HOME > RECORDINGS and select a file. Press the PLUS button and delete.  If you want to delete more than 1 programme, press the PLUS button and select Select. You can mark files and then delete, copy or move the multiple files.
How to edit media files?		Go to HOME > MEDIA CENTER and select Internal HDD. Select a file and press the PLUS button. You can delete, copy or move the file.
Does not recognize larger external HDDs.	HDD capacity is too large.	<ul> <li>HUMAX recommends to use external HDDs up to 1TB.</li> <li>If the external HDD is making a ticking sound or not being recognized, this may indicate that the electricity is not sufficient. Please connect the power cable of the external HDD or connect another USB cable to the product.</li> </ul>

Problem	Possible Cause	What to Do
How to read files from external HDD		<ul> <li>Go to HOME &gt; MEDIA CENTER and select an external HDD. Select a file and press the OK button.</li> <li>Some files may not be played depending on the file format.</li> </ul>
How to delete root folder?		You cannot delete the root folder that is to store the downloaded files.

### Network

Problem	Possible Cause	What to Do
Cannot connect to the Internet	Too far from the wireless router Walls or obstacles between the product and the router cause interference. Faulty Ethernet cable Wrong password	<ul> <li>Check if the network is connected properly. Go to HOME &gt; SETTINGS &gt; Network Settings and select Network Connection Status.</li> <li>If wireless network is not available in your home, use an Ethernet cable to connect the product and the router.</li> <li>Turn off the product and the router and then on to refresh the network.</li> <li>Move the product closer to the wireless router or remove any obstacles from between them.</li> <li>If you use an Ethernet cable, changing the Ethernet cable.</li> <li>Check if other network devices in the same network are connecting to the internet okay.</li> <li>Check the network password.</li> <li>Note:</li> <li>The home network environment may cause the Internet speed slow down.</li> </ul>
TV APPS does not work.		Check if the network is connected properly. Go to HOME > SETTINGS > Network Settings and select Network Connection Status. If not connected, refer to the troubleshooting guide for the network.  Note: Network traffic may cause temporary loss of network connectivity. Poor network connection may cause TV APPS run slowly.
Cannot play YouTube video.	Some YouTube videos are played on PC only.	Play another video to view.

## Media Center

Problem	Possible Cause	What to Do
Cannot find mobile devices in the network	Network is not connected.  Firewall may be blocking the access.	<ul> <li>Check if the network is connected properly. Go to HOME &gt; SETTINGS &gt; Network Settings and select Network Connection Status.</li> <li>If wireless network is not available in your home, use an Ethernet cable to connect the product and the router.</li> <li>Turn off the product and the router and then on to refresh the network.</li> <li>Check if your mobile device is DLNA compatible.</li> <li>Make sure that your product and mobile devices are in the same network.</li> <li>Note</li> <li>The home network environment may cause the Internet speed slow down.</li> </ul>
Network server does not work	HUMAX product is not connected to the network or the network is not configured.  Home network devices are not connected to the network or the network is not configured.  PC/Router settings are not correct.	<ul> <li>Go to HOME &gt; SETTINGS &gt; Network settings and check if Network Server is set to On. When the network server option is set to on, files stored in the internal HDD can be shared with other DLNA compliant devices in the same network.</li> <li>Make sure that the options to share media files are enabled on your PC.</li> <li>Check if any firewall settings on your PC or router blocks DLNA compatibility.</li> </ul>
Remote Recording	HUMAX product is not registered.  IP EPG is not activated.  HUMAX product is not paired with mobile devices.	<ul> <li>Make sure that your product is registered in myhumax.net. Go to HOME &gt; SETTINGS &gt; PVR Settings and set IP EPG to On and Remote Recording to On.</li> <li>Make sure that your product is paired with mobile device.</li> <li>Make sure that the current time is within the update period. Go to HOME &gt; SETTINGS &gt; PVR Settings &gt; Remote Recording and set the update period.</li> <li>Check the update interval. Go to HOME &gt; SETTINGS &gt; PVR Settings &gt; Remote Recording and set the update interval.</li> <li>Make sure that your product is turned on or in standby mode.</li> </ul>
File share(SAMBA/FTP) does not work	Network connection error File sharing options	<ul> <li>Check if the network is connected properly. Go to HOME &gt; SETTINGS &gt; Networks Settings and select Network Connection Status.</li> <li>Make sure that your product and PCs are in the same network.</li> <li>Make sure that the SAMBA server is activated. Go to HOME &gt; SETTINGS &gt; Network Settings &gt; File Share and set SAMBA Server to On.</li> <li>Make sure that the FTP server is activated. Go to HOME &gt; SETTINGS &gt; Network Settings &gt; File Share and set FTP Server to On.</li> <li>Check if the password is correct. Go to HOME &gt; SETTINGS &gt; Network Settings &gt; File Share and set a new password.</li> </ul>

#### Others

Problem	Possible Cause	What to Do
Can I use a HUMAX product from other countries in Australia?	Each country has their own broadcasting system. HUMAX product is made it possible for regional broadcasting environment.	HUMAX products from other countries are not available in Australia. Customer services may be limited.

Cautions: Electromagnetic interferences from other electronic devices or cables may cause malfunction to the HUMAX product.

## **HUMAX Customer Support**

More information on your product is provided in the HUMAX website. Should your product require warranty service, please contact Humax Australia Service.

Tel: Opening Hours: Address: E-mail: Website: Language:	1300 737 937 Mon-Fri 9:00-17:00 AEST (excluding Public Holidays) 9 / 602 Whitehorse Road, Mitcham, Vic, 3132 ausupport@humaxdigital.com www.humaxdigital.com/au English
---	---

## Glossary

#### CVBS (Composite Video Baseband Signal)

A technology for transmitting video signals via a cable. Mixes luminance (brightness) and the chrominance (colour) signals together.

#### **Dolby Digital**

An encoding system that digitally compresses up to 5.1 discrete channels of audio (left front, centre, right front, left surround, right surround) into a single Bitstream. A low frequency effect (LFE) channel is included providing the sound needed for special effects.

#### DVB (Digital Video Broadcasting)

A set of standards that define digital broadcasts using satellite, cable or terrestrial systems.

#### EPG (Electronic Program Guide)

An electronic equivalent to a printed television listings magazine. It is an application used with digital set-top boxes and digital television sets to list current and scheduled programs that are or will be available on each channel, including a short summary or commentary for each Program. The information supplied in the EPG is sent and updated by the channel broadcaster.

#### Frequency

The property of a signal measured in cycles per second (=Hz).

#### FTA (Free-To-Air)

An unscrambled broadcaster allowing customers to view channels or services without paying any subscription.

#### HDD (Hard Disk Drive)

The primary computer storage medium, which is made of one or more aluminum or glass platters, coated with a ferromagnetic material.

#### HDMI (High-Definition Multimedia Interface)

An all-digital audio/video interface that supports standard, enhanced, or high-definition video, plus multi-channel digital audio on a single cable. It transmits all ATSC HDTV standards and supports 8-channel digital audio.

#### OTA (Over the Air)

A standard for the transmission of software for equipment, through a broadcast system. Manufacturers reserve the right for deciding the release of the software for their products.

#### PVR (Personal Video Recorder)

A video recorder that can record and play back programs directly using the internal hard disk drive(s).

#### RF (Radio Frequency)

Television signals are modulated onto RF signals and are then demodulated by the tuner of your TV or STBs.

#### RGB (Red - Green - Blue)

A technology for transmitting video signals via a cable. RGB is a system to represent red, green, and blue colours on a TV or monitor display. Red, green, and blue can be combined in various proportions to obtain any colour.

#### S/PDIF (Sony/Philips Digital Interface format)

A standard format for the transfer of digital audio signals. It allows the transfer of digital audio between two devices without any conversion to and from analogue, which could degrade the signal quality.

#### S-Video (Super-Video)

Sometimes referred to as Y/C video; a technology for transmitting video signals via a cable. It is a video signal transmission in which the luminance (brightness) and the chrominance (colour) signals are transmitted separately to achieve superior picture clarity.

#### TSR (Time Shifted Recording)

A function that records the present program temporarily to support trick-play.

#### Open Source Software Notice

HUMAX products use certain open source operating system software distributed pursuant to GNU GENERAL PUBLIC LICENSE Version 2 and GNU I FSSFR GENERAL LICENSE Version 2.1 each as defined and published by the Free Software Foundation, Inc.

The following GPL and LGPL software source codes used in this product can be provided and this offer is valid for up to three years from the date of original download of the software or purchase of product containing such software. Please contact us at gnu@humaxdigital.com.

#### GPI Software

busybox lihext2fs compiler

e2fsprogs mtdutile

dosfstools samba proftpd

#### I GPL Software

uClibo ffmpea

#### FreeType License (FTL) Software

Portions of this software are copyright © <2007> The FreeType Project All rights reserved.

#### OpenSSI License Software

This product includes cryptographic software written by Eric Young.(eav@ cryptsoft.com)

This product includes software written by Tim Hudson. (tih@cryptsoft.com)
This product includes software developed by the OpenSSL Project for use in the OpenSSL Toolkit.(http://www.openssl.org)

Use, modification and redistribution of the Open Source Software is governed by the terms and conditions of the applicable Open Source License. The GNU General Public License (GPL) v2 is shown below.

#### The GNU General Public License (GPL)

Version 2, June 1991

Copyright (C) 1989, 1991 Free Software Foundation, Inc.51 Franklin Street, Fifth Floor, Boston, MA 02110-1301, USA Everyone is permitted to copy and distribute verbatim copies of this license document, but changing it is not allowed

#### Preamble

Preamble
The licenses for most software are designed to take away your freedom to share and change it. By contrast, the GNU General Public License is intended to guarantee your freedom to share and change free software—to make sure the software is free for all its users. This General Public License applies to most of the Free Software Foundation's software and to any other program whose authors committed using it. (Some other Free Software Foundation software is covered by the GNU Lesser General Public License instead.) You can apply it to your programs, too. When we speak of free software, we are referring to freedom, not price, Our General Public Licenses are designed to make sure that you have the freedom to distribute copies of free software (and charge for this service if you wish), that you receive source code or can get it if you want it, that you can change the software or use pieces of it in new free programs; and that you know you can do these things. To protect your rights, we need to make restrictions that forbid anyone to

deny you these rights or to ask you to surrender the rights. These restrictions translate to certain responsibilities for you if you distribute copies of the software, or if you modify it.

For example, if you distribute copies of such a program, whether gratis or for a fee, you must give the recipients all the rights that you have. You must make sure that they, too, receive or can get the source code. And you must show them these terms so they know their rights.

We protect your rights with two steps: (1) copyright the software, and (2) offer you this license which gives you legal permission to copy, distribute and/or

Also, for each author's protection and ours, we want to make certain that everyone understands that there is no warranty for this free software. If the software is modified by someone else and passed on, we want its recipients to know that what they have is not the original, so that any problems introduced by others will not reflect on the original authors' reputations.

Finally, any free program is threatened constantly by software patents. We wish to avoid the danger that redistributors of a free program will individually obtain patent licenses, in effect making the program proprietary. To prevent this, we have made it clear that any patent must be licensed for everyone's

free use or not licensed at all.

The precise terms and conditions for copying, distribution and modification

#### TERMS AND CONDITIONS FOR COPYING, DISTRIBUTION AND MODIFICA-

TERMO AND CONDITIONS PORCOPTING, DISTRIBUTION AND INCOME.

On This License applies to any program or other work which contains a notice placed by the copyright holder saying it may be distributed under the terms of this General Public License. The "Program", below, refers to any such program or work, and a work based on the Program "means either the Program or any derivative work under copyright and that the is to say, a work containing the Program or a protein of it, either verballing with modifications and of the Program or any derivative work under copyright are that the program or any derivative work with modifications and of the Program or any deviation of the program or any deviation of the program of the program or any deviation of the program of the pro Activities other than copying, distribution and modification are not covered by this License: they are outside its scope. The act of running the Program is not restricted, and the output from the Program is covered only if its contents constitute a work based on the Program (independent of having been made by running the Program). Whether that is true depends on what

the Program does. . You may copy and distribute verbatim copies of the Program's source code as you receive it, in any medium, provided that you conspicuously and appropriately publish on each copy an appropriate copyright notice and disclaimer of warranty; keep intact all the notices that refer to this License and to the absence of any warranty, and give any other recipients of the Program a copy of this License along with the Program. You may charge a fee for the physical act of transferring a copy, and you may at your option offer warranty protection in exchange for a fee

You may modify your copy or copies of the Program or any portion of it, thus forming a work based on the Program, and copy and distribute such modifications or work under the terms of Section 1 above, provided that you also meet all of these conditions

a) You must cause the modified files to carry prominent notices stating that you changed the files and the date of any change.

b) You must cause any work that you distribute or publish, that in whole or in part contains or is derived from the Program or any part thereof, to be licensed as a whole at no charge to all third parties under the terms of

 If the modified program normally reads commands interactively when run, you must cause it, when started running for such interactive use in the most ordinary way, to print or display an announcement including an appropriate copyright nótice and a notice that there is no warranty (or else, saying that you provide a warranty) and that users may redistribute the program under these conditions, and telling the user how to view a copy of this License. (Exception: if the Program itself is interactive but does not normally print such an announcement, your work based on the Program is not required to print an announcement)

These requirements apply to the modified work as a whole. If identifiable s tions of that work are not derived from the Program, and can be reasonably considered independent and separate works in themselves, then this License, and its terms, do not apply to those sections when you distribute them as separate works. But when you distribute the same sections as part of a whole which is a work based on the Program, the distribution of the whole must be on the terms of this License, whose permissions for other licensees extend to he entire whole, and thus to each and every part regardless of who wrote it. hus, it is not the intent of this section to claim rights or contest your rights to work written entirely by you; rather, the intent is to exercise the right control the distribution of derivative or collective works based on the rogram. In addition, mere aggregation of another work not based on the Program with the Program (or with a work based on the Program) on a volume of a storage of distribution medium does not bring the other work

under the scope of this License. You may copy and distribute the Program (or a work based on it, under Section 2) in object code or executable form under the terms of Sections 1 and 2 above provided that you also do one of the following a) Accompany it with the complete corresponding machine-readable source

code, which must be distributed under the terms of Sections 1 and 2 above on a medium customarily used for software interchange; or, b) Accompany it with a written offer, valid for at least three years, to give any third party, for a charge no more than your cost of physically performing source distribution, a complete machine-readable copy of the corresponding source code, to be distributed under the terms of Sections 1 and 2 above on

a medium customarily used for software interchange; or c) Accompany it with the information you received as to the offer to distribute corresponding source code. (This alternative is allowed only for noncommercial distribution and only if you received the program in object code or executable form with such an offer, in accord with Subsection b above.) The source code for a work means the preferred form of the work for making modifications to it. For an executable work, complete source code means all the source code for all modules it contains, plus any associated interface definition files, plus the scripts used to control compilation and installation of the executable. However, as a special exception, the source code distributed need not include anything that is normally distributed (in either source or binary form) with the major components (compiler, kernel, and so on) of the operating system on which the executable runs, unless that component itself accompanies the executable. If distribution of executable or object code is made by offering access to copy from a designated place.

then offering equivalent access to copy the source code from the same place. INCIDENTAL OR CONSPOLIENTIAL DAMAGES ARISING OF THE LISE OR counts as distribution of the source code, even though third parties are not compelled to copy the source along with the object coo

4. You may not copy, modify, sublicense, or distribute the Program except as expressly provided under this License. Any attempt otherwise to copy. modify, sublicense or distribute the Program is void, and will automatically terminate your rights under this License However, parties who have received FND OF TERMS AND CONDITIONS. copies, or rights, from you under this License will not have their licenses erminated so long as such parties remain in full compliance

You are not required to accept this License, since you have not signed it However, nothing else grants you permission to modify or distribute the Program or its derivative works. These actions are prohibited by law if you do. not accept this License. Therefore, by modifying or distributing the Program (or any work based on the Program), you indicate your acceptance of this License to do so, and all its terms and conditions for copying, distributing or modifying the Program or works based on it.

6. Each time you redistribute the Program (or any work based on the Program), the recipient automatically receives a license from the original licensor to copy, distribute or modify the Program subject to these ferms and conditions. You may not impose any further restrictions on the recipients' exercise of the rights granted herein. You are not responsible for enforcing compliance by third parties to this License

7. If, as a consequence of a court judgment or allegation of patent infringe-ment or for any other reason (not limited to patent issues), conditions are imposed on you (whether by court order, agreement or otherwise) that contradict the conditions of this License, they do not excuse you from the conditions of this License. If you cannot distribute so as to satisfy simultaneously. your obligations under this License and any other pertinent obligations, then as a consequence you may not distribute the Program at all. For example, if a patent license would not permit royalty-free redistribution of the Program by all those who receive copies directly or indirectly through you, then the only way you could satisfy both it and this License would be to refrain entirely from distribution of the Program. If any portion of this section is held invalid or unenforceable under any particular circumstance, the balance of the section is intended to apply and the section as a whole is intended to apply in other circumstances. It is not the purpose of this section to induce you to infringe any patents or other property right claims or to contest validity of any such claims: this section has the sole purpose of protecting the integrity of the free software distribution system, which is implemented by public license. practices. Many people have made generous contributions to the wide range of software distributed through that system in reliance on consistent application of that system; it is up to the author/donor to decide if he or she is willing to distribute software through any other system and a licensee cannot impose that choice

This section is intended to make thoroughly clear what is believed to be a consequence of the rest of this License.

If the distribution and/or use of the Program is restricted in certain countries either by patents or by copyrighted interfaces, the original copyright holder who places the Program under this License may add an explicit geographical distribution limitation excluding those countries, so that distribution is permitted only in or among countries not thus excluded. In such case, this icense incorporates the limitation as if written in the body of this License The Free Software Foundation may publish revised and/or new versions of the General Public License from time to time. Such new versions will be similar in spirit to the present version, but may differ in detail to address new

Each version is given a distinguishing version number. If the Program specifies a version number of this License which applies to it and "any later version". you have the option of following the terms and conditions either of that yer sion or of any later version published by the Free Software Foundation. If the Program does not specify a version number of this License, you may choose

any version ever published by the Free Software Foundation.

10. If you wish to incorporate parts of the Program into other free programs whose distribution conditions are different, write to the author to ask for permission. For software which is copyrighted by the Free Software Foundation, write to the Free Software Foundation; we sometimes make exceptions for this. Our decision will be guided by the two goals of preserving the free status of all derivatives of our free software and of promoting the sharing and reuse of software generally.

#### NO WARRANTY

11. BECAUSE THE PROGRAM IS LICENSED FREE OF CHARGE, THERE IS NO WARRANTY FOR THE PROGRAM, TO THE EXTENT PERMITTED BY APPLICABLE LAW, EXCEPT WHEN OTHERWISE STATED IN WRITING THE COPYRIGHT HOLDERS AND/OR OTHER PARTIES PROVIDE THE PROGRAM "AS IS" WIT WARRANTY OF ANY KIND, EITHER EXPRESSED OR IMPLIED, INCLUDING. BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, THE ENTIRE RISK AS TO THE QUALITY AND PERFORMANCE OF THE PROGRAM IS WITH YOU. SHOULD THE PROGRAM PROVE DEFECTIVE, YOU ASSUME THE COST OF ALL NECESSARY SERVICING, REPAIR OR CORRECTION.

12. IN NO EVENT UNLESS REQUIRED BY APPLICABLE LAW OR AGREED TO IN WRITING WILL ANY COPYRIGHT HOLDER, OR ANY OTHER PARTY WHO MAY MODIFY AND/OR REDISTRIBUTE THE PROGRAM AS PERMITTED ABOVE. BE LIABLE TO YOU FOR DAMAGES, INCLUDING ANY GENERAL, SPECIAL,

INABILITY TO USE THE PROGRAM (INCLUDING BUT NOT LIMITED TO LOSS OF DATA OR DATA BEING RENDERED INACCURATE OR LOSSES SUSTAINED YOU OR THIRD PARTIES OR A FAILURE OF THE PROGRAM TO OPERATE ANY OTHER PROGRAMS), EVEN IF SUCH HOLDER OR OTHER PARTY HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES

How to Apply These Terms to Your New Programs

f you develop a new program, and you want it to be of the greatest possible use to the public, the best way to achieve this is to make it free software which everyone can redistribute and change under these terms. To do so, attach the following notices to the program. It is safest to attach them to the start of each source file to most effectively convey the exclusion of warranty; and each file should have at least the "copyright" line and a pointer to where the full notice is found.

One line to give the program's name and a brief idea of what it does. Copyright (C) yww\_name of author This program is free software; you can redistribute it and/or modify it under the terms of the GNU General Public License as published by the Free Software Foundation; either version 2 of the License, or (at your option) any later version. This program is distributed in the hope that it will be useful, but WITHOUT ANY WARRANTY; without even the implied warranty of MERCHANTABILITY or FITNESS FOR A PARTICULAR PUR-POSE. See the GNU General Public License for more details. You should have received a copy of the GNU General Public License along with this program: i not, write to the Free Software Foundation, Inc., 51 Franklin Street, Fifth Floor, Boston, MA 02110-1301, USA. Also add information on how to contact you by electronic and paper mail. If the program is interactive, make it output a short notice like this when it starts in an interactive mode:

Gnomovision version 69, Copyright (C) year name of author Gnomovision comes with ABSOLUTELY NO WARRANTY: for details type 'show w/. This is free software, and you are welcome to redistribute it under certain conditions; type 'show c' for details

The hypothetical commands 'show w' and 'show c' should show the appropriate parts of the General Public License. Of course, the commands you use may be called something other than 'show w' and 'show c': they could even be mouse-clicks or menu items-whatever suits your program. You should also get your employer (if you work as a programmer) or your school, if any, to sion a "copyright disclaimer" for the program, if necessary. Here is a sample: alter the names:

Yoyodyne. Inc., hereby disclaims all copyright interest in the program Gnomovision' (which makes passes at compilers) written by James Hacker. signature of Tv Coon, 1 April 1989.

v Coon. President of Vice his General Public License does not permit incorporating your program. into proprietary programs. If your program is a subroutine library, you may consider it more useful to permit linking proprietary applications with the library. If this is what you want to do, use the GNU Library General Public License instead of this License.

#### GNU Lesser General Public License (LGPL) Version 2.1, February 1999

Version 2.1,7 leading 1999 Free Software Foundation, Inc. 51 Franklin Street, Fifth Floor, Boston, MA 02110-1301 USA Everyone is permitted to copy and distribute verbatim copies of this license document, but changing it

This is the first released version of the Lesser GPL. It also counts as the successor of the GNU Library Public License, version 2, hence the version

The licenses for most software are designed to take away your freedom to share and change it. By contrast, the GNU General Public Licenses are intended to guarantee your freedom to share and change free software—to make sure the software is free for all its users.

This license, the Lesser General Public License, applies to some specially designated software packages—typically libraries—of the Free Software Foundation and other authors who decide to use it. You can use it too. but we suggest you first think carefully about whether this license or the ordinary General Public License is the better strategy to use in any particular case, based on the explanations below. When we speak of free software, we are referring to freedom of use, not price. Our General Public Licenses are designed to make sure that you have the freedom to distribute copies of free software (and charge for this service if you wish); that you receive source code or can get it if you want it: that you can change the software and use pieces of it in new free programs; and that you are informed that you can do these things. To protect your rights, we need to make restrictions that forbid distributors to deny you these rights or to ask you to surrender these rights. of the library, whether gratis or for a fee, you must give the recipients all the of the library or if you modify it. For example, if you distribute copies of the library or if you modify it. For example, if you distribute copies of the library, whether gratis or for a fee, you must give the recipients all the on the invary, which fire grats or for a fee, your must give the reophents all the rights that the gave you. You must make sure that they, too, receive or can get the source code. If you link other code with the library, you must provide complete object files to the recipients, so that they can relink them with the library after making changes to the library and recompiling it. And you must. show them these terms so they know their rights. We protect your rights with a two-step method: (1) we copyright the library, and (2) we offer you this li-cense, which gives you legal permission to copy, distribute and/or modify the library. To protect each distributor, we want to make it very clear that there is no warranty for the free library. Also, if the library is modified by someone else and passed on, the recipients should know that what they have is not the original version, so that the original author's reputation will not be affected by

problems that might be introduced by others. Finally, software patents pose a constant threat to the existence of any free program. We wish to make sure that a company cannot effectively restrict the users of a free program by obtaining a restrictive license from a patent holder. herefore, we insist that any patent license obtained for a version of the library must be consistent with the full freedom of use specified in this license Most GNU software, including some libraries, is covered by the ordinary GNU General Public License This license, the GNU Lesser General Public License. applies to certain designated libraries, and is guite different from the ordinary General Public License. We use this license for certain libraries in order to permit linking those libraries into non-free programs. When a program is linked with a library, whether statically or using a shared library, the combination of the two is legally speaking a combined work, a derivative of the original library. The ordinary General Public License therefore permits such linking only if the entire combination fits its criteria of freedom. The Lesser General Public License permits more lax criteria for linking other code with the library. We call this license the "Lesser" General Public License because it does Less to protect the user's freedom than the ordinary General Public License It. also provides other free software developers Less of an advantage over competing non-free programs. These disadvantages are the reason we use the ordinary General Public License for many libraries. However, the Lesser icense provides advantages in certain special circumstances. For example, on rare occasions, there may be a special need to encourage the widest possible use of a certain library, so that it becomes a de-facto standard. To achieve this non-free programs must be allowed to use the library. A more frequent case is that a free library does the same job as widely used non-free libraries. In this case, there is little to gain by limiting the free library to free software only, so we use the Lesser General Public License. In other cases, permission to use a particular library in non-free programs enables a greater number of people o use a large body of free software. For example, permission to use the GNU C Library in non-free programs enables many more people to use the whole GNU operating system, as well as its variant, the GNU/Linux operating system Although the Lesser General Public License is Less protective of the users freedom, it does ensure that the user of a program that is linked with the Library has the freedom and the wherewithal to run that program using a modified version of the Library. The precise terms and conditions for copying, distribution and modification follow. Pay close attention to the difference between a "work based on the library" and a "work that uses the library". The former contains code derived from the library, whereas the latter must be combined with the library in order to run

#### TERMS AND CONDITIONS FOR COPYING, DISTRIBUTION AND MODIFICA-

0. This License Agreement applies to any software library or other program This License Agreement applies to any software library of unit program which contains a notice placed by the copyright holder or other authorized party saying it may be distributed under the ferms of this Lesser General Public License (also called "this License"). Each licensee is addressed as "you". A "library" means a collection of software functions and/or data prepared so as to be conveniently linked with application programs (which use some of those functions and data) to form executables. The "Library", below, refers to any such software library or work which has been distributed under these terms. A "work based on the Library" means either the Library or any derivative work under convright law that is to say, a work containing the Library or a portion of it, either verbatim or with modifications and/or translated straightforwardly into another language. (Hereinafter, translation is included without limitation in the term "modification") "Source code" for a work means the preferred form of the work for making modifications to It. For a library. complete source code means all the source code for all modules it contain plus any associated interface definition files, plus the scripts used to control compilation and installation of the library. Activities other than copying, distribution and modification are not covered by this License; they are outside its scope. The act of running a program using the Library is not restricted, and output from such a program is covered only if its contents constitute a work based on the Library (independent of the use of the Library in a tool for writing it). Whether that is true depends on what the Library does and what the program that uses the Library does.

1. You misy copy and distribute verbatim copies of the Library complete source code as you needve it, in any medium, provided that you conspicuously and appropriately publish on each copy an appropriate copyright notice and disclaiment of warranty, been intent all the notices that refer to this License and to the absence of any warranty, and distribute a copy of this License along with the Library. You may charge a fee for the physical act of transferring a copy, and you may at your option offer warranty protection in exchange for a fee.

 You may modify your copy or copies of the Library or any portion of it, thus forming a work based on the Library, and copy and distribute such modifications or work under the terms of Section 1 above, provided that you also meet all of these conditions

a) The modified work must itself be a software library.

b) You must cause the files modified to carry prominent notices stating that you changed the files and the date of any change.

() You must cause the whole of the work to be licensed at no charge to all

third parties under the terms of this License

d) If a facility in the modified Library refers to a function or a table of data to be supplied by an application program that uses the facility, other than as an argument passed when the facility is invoked, then you must make a good afth effort to ensure that, in the event an application does not supply such function or table, the facility still operates, and performs whatever part of its purpose remains meaningful. (For example, a function in a library to compute square roots has a purpose that is entirely well-defined independent of the application. Therefore, Subsection 2d requires that any application-supplied unction or table used by this function must be optional: if the application does not supply it, the square root function must still compute square roots.) These requirements apply to the modified work as a whole If identifiable sections of that work are not derived from the Library, and can be reasonably considered independent and separate works in themselves, then this License and its terms, do not apply to those sections when you distribute them as separate works. But when you distribute the same sections as part of a whole which is a work based on the Library, the distribution of the whole must be on the terms of this License, whose permissions for other licensees extend to he entire whole, and thus to each and every part regardless of who wrote it Thus, it is not the intent of this section to claim rights or contest your rights to work written entirely by you; rather, the intent is to exercise the right to control the distribution of derivative or collective works based on the Library In addition, mere aggregation of another work not based on the Library with the Library (or with a work based on the Library) or distribution medium does not bring the other work under the scope of

3. You may opt to apply the terms of the ordinary GNU General Public Lucense instead of this License to a given copy of the Library. To do this, you must after all the notices that refer to this License, but they refer to the ordinary GNU General Public License (than every everyon than vestion 2 of the ordinary GNU General Public License (than every everyon than vestion 2 of the ordinary GNU General Public License (than every everyon than vestion 2 of the ordinary GNU General Public License that appeared, then you can specify that vestion instead if you wish 10 not not take you will not not take the young that they have the compared to the public than the young that they will be a public to the young that they will be a public than the young that they will be a public than the young that they will be a public than the young that they will be a public than the young that they will be a public that

4 You may copy and distribute the Library for a portion or derivative of it, under section 2 in object code or executable form under the terms of sections 1 and 2 above provided that you accompany it with the complete corresponding machine-readable source code which must be distributed under the terms of Sections 1 and 2 above on a medium customarily used for software interchange if distribution of object code is made by offering access to copy the source code from the same place; satisfies the requirement to distribute the source code, even though third parties are not compelled to copy the source along with the object code.

5. A frogram that contains no delivative of any portion of the Library, but is designed to work with the Library by being complied or linked with it is called a "work that uses the Library," Such a work, in Isolation, is not a derivative work of the Library, and therefore falls outside the scope of this Licrose. However, linking a "work that uses the Library" with the Library creates an executable that as derivative of the Library (because it contains portions of the Library), rather than a work that uses the library. The executable is a derivative of the Library (because it contains portions of the Library), rather than a work that uses the library. The executable is which ever failed in the contains the conta

When a 'work that uses the Libray' uses material from a header file that is part of the Libray, the object code for the work may be a derivative work of the Library even though the source code is not. Whether this is true is especially significant if the work can be linked without the Library or if the work is steal alibrary. The threshold for this to be true is not precisely defined by law. If such nobject file uses only numerical parameters, data structure layouts and accessors, and small macros and small inline functions (ten lines of vless in length), then the use of the object file is unestricted, reparadict of whether it is legally a derivative work. (Executables containing this object code plus portions of the Libray will still fall under Section 6).

Otherwise, if the work is a derivative of the Library, you may distribute the object code for the work under the terms of Section 6. Any executables containing that work also fall under Section 6, whether or not they are linked directly with the Library itself:

6. As an exception to the Sections above, you may also combine of link a Work that uses the Library win the Library to produce a work, containing portions of the Library, and distribute that work under terms of your choice, provided that the terms permit morphication of the work for the customer's own use and reverse engineering for debuggings such modifications. You must give prominent notice with each copy of the work that the Library is used in and that the Library and its use are overed by this Library is used in and that the Library and its use are overed by this Library and the Library and

a) Accompany the work with the complete corresponding machine-readable source code for the Library including whatever changes were used in the work (which must be distributed under Sections 1 and 2 above); and, if the work is an executable linked with the Library, with the complete machine-

readable work that uses the Library, as object code and/or source code, so that the user can modify the Library and the mellink to produce a modified executable containing the modified Library, it is undestood that the user who changes the conferest of definitions files in the Library will not necessarily be able to recomplie the application to use the modified definitions), by Use a suitable shared library mechanism for linking with the Library. A suitable mechanism is one that (I) uses at runnine a copy of the library already into the executable, and (2) will operate properly with a modified version of the library, if the user installs one, as long as the modified version is interface-compatible with the version that the work was made with.

c) Accompany the work with a written offer, valid for at least three years, to give the same user the materials specified in Subsection 6a, above, for a charge no more than the cost of performing this distribution, all if distribution of the work is made by offering access to copy from a designated place, offer equivalent access to copy the above specified materi-

als from the same place. e) Verify that the user has already received a copy of these materials or that

you have already sent this user a copy.

For an escutable, the required form of the York that uses the Library must include any data and utility programs needed for reproducing the escentable from it. However, as a special exception, the materials to be distributed need not include anything that is normally distributed (in either source or briary form with the majet components (compiler, lernel, and so of) of the companies the executable.

It You may ont to apply the terms of the ordinary GNU General Public License. It may happen that this requirement contacts the license restrictions of instead of this License to a given copy of the Library To do this you must alter other proprietary libraries that for normally accompany the operating all the notices that refer to this License, so that they refer to the ordinary GNU system Such a contradiction means you cannot use both them and the seneral Public License version 2. Instead of to this License. If a newer version is not on the Lindary to describe that you distribute that you distribute that you distribute.

7. You may place library facilities that are a work based on the Library side. Possible in a single library together with other library facilities not covered by this License, and distribution of the work based on the Library and off the other library lated distribution of the work based on the Library and off the other library lated is in otherwise permitted, and provided that you do these two things:
a) Accompany the combined library with a copy of the same work based on the Library, uncombined with any other library facilities. This must be distributed under the terms of the Sections above.

b) Give prominent notice with the combined library of the fact that part of it is a work based on the Library, and explaining where to find the accompanying uncombined form of the same work.

8. You may not copy, modify, sublicense link with, or distribute the Libray except as expressly provided under this Liernes. Any attempt of herewise to copy, modify, sublicense, link with, or distribute the Libray is void, and will automatically terminate your rights under this Liernes. However, parties who have received copies, or rights, from you under this License Miller and the licenses terminated so long as such parties emain in full compliance.

9. You are not required to accept this License, since you have not signed it. However, nothing else grants you permission to modify or distribute the Libray or its derivative works. These actions are prohibited by Jaw If you do not accept this License are prohibited by Jaw If you do not accept that Ecrose's Therefore, by modifying or distributing the Libray for the properties of the subject of dosp, and all list terms and conditions for copying, distributing or modifying the libray low roughly and the properties of the pro

10. Each time you redistribute the Library (or any work based on the Library), the recipient automatically receives a license from the original licensor to copy, distribute, link with or modify the Library subject to these terms and conditions. You may not impose any further restrictions on the recipients' exercise of the rights granted the herein. You are not responsible for enforcing the precipions are not responsible for enforcing the precipions.

exercise of the rights granted herein. You are compliance by third parties with this License.

11. If, as a consequence of a court judgment or allegation of patent infringement or for any other reason (not limited to patent issues), conditions are imposed on you (whether by court order, agreement or otherwise) that contradict the conditions of this License, they do not excuse you from the conditions of this License. If you cannot distribute so as to satisfy simultane. ously your obligations under this License and any other pertinent obligations then as a consequence you may not distribute the Library at all. For example, if a patent license would not permit royalty-free redistribution of the Library by all those who receive copies directly or indirectly through you, then the only way you could satisfy both it and this License would be to refrain entirely from distribution of the Library. If any portion of this section is held invalid or nunenforceable under any particular circumstance, the balance of the section is intended to apply, and the section as a whole is intended to apply in other circumstances. It is not the purpose of this section to induce you to infringe any patents or other property right claims or to contest validity of any such claims; this section has the sole purpose of protecting the integrity of the free software distribution system which is implemented by public license practices. Many people have made generous contributions to the wide range of software distributed through that system in reliance on consistent application of that system in the property of the system of the system in the property of the system of the system in the property of the system of the willing to distribute software through any other system and a licensee cannot impose that choice. This section is intended to make thoroughly clear what is believed to be a consequence of the rest of this License. 12. If the distribution and/or use of the Library is restricted in certain countries either by patents or by copyrighted interfaces, the original copyright holder

who places the Library under this License may add an explicit geographical distribution limitation excluding these countries, so that distribution is the License proof of the properties of the License proof properties the limitation as it written in the body of this License. It is the limitation as it written in the body of this License. 13. The Free Software Foundation may publish revised and/or new versions of the Lesser General Public License from time to time. Such new versions will be similar in spirit to the present version, but may differ in detail to address new voroblems or concerns.

Each version is given a distinguishing version number if the Library specifies a version number of this License which applies to it and 'any later version', you have the option of following the terms and conditions either of that version or of any later version published by the Tree Software Foundation. If the Library does not specify a license version number, you may choose any version eyer unlikhed by the Tree Software Foundation.

14. If you wish to incorporate parts of the Libray into other free programs whose distribution conditions are incompatible with these, write to the author to ask for permission. For software evhich is copyrighted by the Free Software Foundation, write to the Free Software Foundation, write to the Free Software Foundation, write to the Free Software Foundation, we goals of the company of the software and the guided by the two goals of many of the software and office of the software and office of promoting the software and reuse of software generally.

#### NO WARRANTY

IN OWARRANITY

IN OWARRANITY

IN SECAUSE THE LIBRARY IS LICENSED FREE OF CHARGE THERE IS NO
WARRANITY FOR THE LIBRARY, TO THE EXTENT PERMITTED
WARRANITY FOR THE LIBRARY, TO THE EXTENT PERMITTED
WARRANITY FOR THE LIBRARY STATE DIN WRITING THE COPYRIGHT
WARRANITY OF ANY KIND, ETHER EXPRESSED OR MAPLED INVOLUDING, BUT
WARRANITY OF ANY KIND, ETHER EXPRESSED OR MAPLED INVOLUDING, BUT
WARRANITY OF ANY KIND, ETHER EXPRESSED OR MAPLED INVOLUDING, BUT
WARRANITY OF ANY KIND, ETHER EXPRESSED OR MAPLED INVOLUDING, BUT
WARRANITY OF ANY KIND, ETHER EXPRESSED OR MAPLED INVOLUDING, BUT
WARRANITY OF ANY KIND, ETHER EXPRESSED OR MAPLED INVOLUDING, BUT
WARRANITY OF ANY KIND, ETHER EXPRESSED OR MAPLED INVOLUDING, BUT
WARRANITY OF ANY KIND, ETHER
WARRANITY OF ANY KIND, ETHER
WARRANITY OF ANY KIND, BUT
WARRANITY OF

16. IN NO DENT DIM ESS REQUIRED BY APPLICABLE LAW OR AGREED TO INWRITING WILL ANY COPYRIGHT HOLDER OR ANY OTHER PARTY WHO MAY MODIFY AND ANY COPYRIGHT HOLDER OR ANY OTHER PARTY WHO MAY MODIFY AND AND ARE RESTRIBLY THE LIBRARY TO A FERMITTED ABOVE, BELLARLE TO VOLO PER DAMAGES, INCLUDING ANY GENERAL SPECIAL INCIDENTAL OR CONSEQUENTIAL DAMAGES ARISING OUT OF THE USE OR MABILITY TO USE THE LIBRARY MICHALDING BUT NOT LIMITED TO LOSS OF DATA OR DATA BEING SENDERED INACCURATE OR LOSSES SUSTAINED BY VOLO RITHERY PARTIS OR A FALLINE OF THE LIBRARY TO OPERATE WITH ANY OTHER SOFTWARE, LEVEN IF SUCH HOLDER OR OTHER PARTY HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH HOLDER OR OTHER PARTY HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH HOLDER OR OTHER PARTY HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

#### END OF TERMS AND CONDITIONS How to Apply These Terms to Your New Libraries

If you develon a new library, and you want it to be of the greatest possible use to the public, we recommend making it free software that everyone can redistribute and change. You can do so by permitting redistribution under these terms (or, alternatively, under the terms of the ordinary General Public Li lense).

To apply these terms, attach the following notices to the library. It is affest to attach them to the starf of each source file to most effectively convey the exclusion of warranty, and each file should have at least the "copyright line and a pointer to where the full notices found one time to give the library's name and an idea of which it does." Copyright (i) year name of author this, if the start of the control of the c

You should have received a copy of the GNU Lesser General Public License along with this library, firot, write to the Free Software Foundation, Inc., 51 Franklin Street, Fifth Floor, Boston, MA 02110-1301 USA Also add information on how to contact you by electronic and paper mail. You should also your employer (if) you work as a programmen or your school, if any, to Sign 4 copyright disclaimer! for the library, if necessay, Here is a sample; alter

Yoyodyne, Inc., hereby disclaims all copyright interest in the library `Frob' (a library for tweaking knobs) written by James Random Hacker. signature of Ty Coon, 1 April 1990 Ty Coon, President of Vice

## Supplier's declaration of conformity

For compliance levels 1, 2 and 3 in Australia

As required by the following Notices:



- Radiocommunications Labelling (Electromagnetic Compatibility) Notice 2008 made under section 182 of the Radiocommunications Act 1992:
- Radiocommunications (Compliance Labelling Electromagnetic Radiation) Notice 2003 made under section 182 of the Radiocommunications Act 1992; and
- Telecommunications Labelling (Customer Equipment and Customer Cabling) Notice 2001 made under section 407 of the Telecommunications Act 1997

#### Instructions for completion

• Do not return this form to the ACMA. This completed form must be retained by the supplier as part of the documentation required for the compliance records and must be made available for inspection by the ACMA when requested.

#### Supplier's details (manufacturer, importer or authorised agent)

Company Name (OR INDIVIDUAL)
HUMAX Australia Pty Ltd
TRADING AS HUMAX Australia

Street Address

Unit 9,602 Whitehorse rd

MITCHAM

VICTORIA POSTCODE
3132

ACIVIA Supplier code Humber
(issued by the ACMA prior to 1 March 2013)
OP.

OR ABN 22 141 585 882

#### Product details

Product description - brand name, type, model, lot, batch or serial number (if available)

HUMAX		
SET TOP BOX		
HDR-3000T		

#### Compliance

The above mentioned product complies with the requirements of the relevant ACMA Standards made under the Radiocommunications Act 1992 and the Telecommunications Act 1997. These Standards are referenced in notices made under section 182 of the Radiocommunications Act and 407 of the Telecommunications Act.

Evidence of compliance is demonstrated by test reports to the following applicable standards.

#### Applicable standard

Standard title, number and, if applicable, number of the test report

AS/NZS CISPR 13:2012

AS/NZS CISPR 22:2009+A1:2010

#### Declaratio

I hereby declare that the contents of this form are true and correct, that the product mentioned above complies with the relevant above mentioned standards and all products supplied under this declaration will be identical to the product identified above.

**Note**: Under section 137.1 of the Criminal Code Act 1995, it is an offence to knowingly provide false or misleading information to a Commonwealth entity.

Penalty: 12 months imprisonment



[SI BAE]

[R&D General Manager HUMAX R&D Department]

[1st SEPTEMBER 2014]

# **Warranty Certificate**

#### IMPORTANT:

Keep this Certificate together with the Original invoice or receipt in a safe place and show them to the retailer or place of purchase whenever a warranty repair is necessary.

•	Model No.:
•	Serial No.:
•	Date of Purchase:
•	Dealer's Signature:
•	Customer's Signature:

HUMAX thanks you for your recent HUMAX product purchase.

For your benefit, we recommend that you record your serial number, found on the product, and other purchase information on this card and keep it with your personal records, along with proof of purchase. This information will allow us to better serve your needs.

#### **■ WARRANTY CONDITIONS**

Keep this Certificate together with the original invoice or receipt in a safe place and show them to the retailer or place of purchase whenever a warranty repair is necessary.

#### ■ HUMAX CONSUMER WARRANTY

HUMAX warrants this product to be free of defects in materials and workmanship, subject to the conditions set forth overleaf.

#### CONDITIONS

- 1. The HUMAX Warranty is valid for a period of two years from the date of first purchase.
- In the event that this product fails to function properly during the warranty period, the retailer or distributor will make this product capable of operating for the purpose of which it was designed, without charging for labour and parts.
- 3. Our goods come with guarantees that cannot be excluded under the Australian Consumer Law. You are entitled to a replacement or refund for a major failure and for compensation for any other reasonably foreseeable loss or damage. You are also entitled to have the goods repaired or replaced if the goods fail to be of acceptable quality and the failure does not amount to a major failure.
- To make a claim, you are required to contact HUMAX customer service on 1300 737 937.
- This warranty will be honoured only if the Warranty Certificate has been duly completed by the purchaser and is presented to the retailer with the original invoice or receipt.
- The obligations of HUMAX are limited to the repair of defect parts. Costs and risks of transport to the retailer as well as removal and installation of the product, and any other costs directly or indirectly related to its repair, are not covered by the warranty.
- All warranty repairs performed by non-authorized repair shops will not be reimbursed and if such repairs damage this product such damage will not be covered by this warranty.
- 8. This warranty is not applicable in cases other than defects in materials or workmanship and, in particular, does not cover:
  - a. periodic check-ups, adjustments, maintenance or conversions as well as replacement of parts due to normal wear and tear;
  - b. damage caused by accidents, negligence, modifications, use of non-HUMAX parts, improper use, installation or package;
  - damage caused by lightning, water, fire, acts of war, public disturbances, incorrect mains voltages, incorrect ventilation or any other cause beyond the control of the HUMAX.
  - d. products where the label bearing the serial number has been removed, defaced or is illegible.
- This warranty is offered to any person who has legally obtained possession of this product within the warranty period.
- HUMAX's maximum liability shall not exceed the actual purchase price paid by you for the product. In no event shall HUMAX be liable for special, incidental, consequential or indirect damages.

Australia

**Tel:** 1300 737 937

Opening Hours: Mon-Fri 9:00-17:00 AEST (excluding Public Holidays)
Address: 9 / 602 Whitehorse Road, Mitcham, Vic. 3132

E-mail: ausupport@humaxdigital.com
Website: www.humaxdigital.com/au

Language: English